

Ei414



RadioLINK+ Fire/CO Alarm Interface



- Connects Aico domestic alarms to external devices, such as Fire Panel systems, Telecare/Warden Call and Sprinkler systems
- Mains powered with Rechargeable Lithium Back-up
- RadioLINK+ Wireless interconnection
- Key Switch to control on, off and test status
- 5 year guarantee



Description

The Ei414 RadioLINK Fire/CO Alarm Interface connects Aico fire and CO alarms with a range of external devices. The module will receive 'Fire', 'CO' and 'Service' signals from RadioLINK devices and switch the relevant built-in relay

Technical

RF Frequency (MHz)	868.499	RF Range (m)	>100 in free air
Indicators	Green - Power / Red - CO, Fire or Service / Blue - RF transmission	Supply Voltage (V)	230/10-30
Voltage Type	AC/DC	Battery Type	Lithium rechargeable
Technologies	RadioLINK+		

Dimensions & Weights

Depth (mm)	50	Height (mm)	100
Width (mm)	220	Product weight (kg)	0.39
Packaged weight (kg)	0.438		

Approvals & Warranty

Warranty	5 year warranty	EAN Number	5099383005066
-----------------	-----------------	-------------------	---------------

Environmental

Humidity Range (%)	15-95	Temperature Range (°C)	-10 to 40
---------------------------	-------	-------------------------------	-----------